

Table 1: STEVAL-BFA001V2B bill of materials

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	1	STEVAL-IDP005V2		Sensor node	ST	Not available for separate sale
2	1	STEVAL-UKI001V2		Communication adapter board	ST	Not available for separate sale
3	1	STLINK-V3MINI		Programming and debugging interface	ST	STLINK-V3MINI
4	1			Programming cable		
5	1	M12		4-pin female connector	Telemecanique Sensors	XZCP1141L2
					Katlax	CBF12-S44N0-02BPUR
6	1	M12		Male cable mount connector	Telemecanique Sensors	XZCC12MDM40B
					Katlax	CNM12-S4SP0-BP7

Table 2: STEVAL-IDP005V2 bill of materials

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	1	C1	100 nF SMD 0402 50 V ±10%	X7R-Ceramic Capacitor	TDK	C1005X7R1H104K050BB
2	1	C2	3.3 µF SMD 1206 50 V ± 10%	X8L-Ceramic Capacitor	TDK	CGA5L1X8L1H335K160AC
3	5	C3, C5, C6, C19, C31	1 µF SMD 0402 10 V ±10%	X7S-Ceramic Capacitor	Murata	GCM155C71A105KE38D
4	1	C4	22 µF SMD 1210 16 V ±20%	X7R-Ceramic Capacitor	TDK	CGA6P1X7R1C226M250AC
5	1	C7	47 nF SMD 0402 10 V ± 10%	X7R-Ceramic Capacitor	Murata	GRM155R71A473KA01D
6	1	C8	1 µF SMD 0603 50 V ±10%	X5R-Ceramic Capacitor	Murata	GRT188R61H105KE13D
7	9	C9, C10, C11, C12, C23, C26, C44, C45, C48	10 pF SMD 0402 10 V ±1%	C0G-Ceramic Capacitor	Kemet	C0402C100J5GACTU
8	1	C13	SMD 0402 10 V	Capacitor (not mounted)	/	/
9	17	C14, C17, C18, C20, C22, C28, C32, C34, C35, C36, C37, C38, C39, C40, C41, C46, C47	100 nF SMD 0402 10 V ±10%	X7R-Ceramic Capacitor	Würth Elektronik	885012205018
10	1	C15	100 nF SMD 0402 10 V ±10%	X7R-Ceramic Capacitor	Würth Elektronik	885012205018
11	2	C21, C33	4.7 µF SMD 0603 10 V ±10%	X7S-Ceramic Capacitor	TDK	C1608X7S1A475K080AC
12	2	C24, C25	10 pF SMD 0402 50 V ±5%	C0G-Ceramic Capacitor	Kemet	C0402C100J5GACTU

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
13	3	C27, C29, C30	2.2 μ F SMD 0402 10 V \pm 10%	X7R-Ceramic Capacitor	TDK	C1005X7S1A225K050BC
14	2	C42, C43	16 pF SMD 0402 50 V \pm 5%	C0G-Ceramic Capacitor	Murata	GRM1555C1H160JA01D
15	2	D1, D2	NSR05T40P2 SOD-923	Schottky Barrier Diode	OnSemiconduc	NSR05T40P2T5G
16	1	D3	ESDALC6V1-1U2 SMD 0201	Single-line low capacitance Transil™ for ESD protection	ST	ESDALC6V1-1U2
17	1	D4	SMBJ33CA SMB DO-214AA 33V	600 W TVS in SMB	ST	SMBJ33CA
18	1	JP1	IO-Link CONN	IO-Link 4-position M12 A-coded connector	Binder	9043121204
19	1	J1	SMT Pitch 1.27 mm, 5x2	SWD Connector	Harwin	M50-3600542
20	1	J2	TH Pitch 1.27 mm, 5x2	Auxiliary Connector	Harwin	M50-3200545
21	1	L1	68 μ H SMD (4.8x4.8x2.8 mm) Isat = 0.4 A/Rdc = 0.34 ohm \pm 30%	Shielded Power Inductor	Wurth Elektronik	744043680
22	1	R1	1 M SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF1004X
23	3	R2, R22, R23	100 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF1003X
24	1	R3	909 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF9093X
25	1	R4	205 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF2053X
26	1	R5	68 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF6802X
27	1	R6	100 k SMD 0402 0.1 W \pm 1%	Resistor (not mounted)	/	/
28	2	R7, R8	4 k7 SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2GEJ472X
29	5	R9, R10, R11, R13, R25	100 R SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF1000X
30	1	R12	22 k SMD 0603 0.1 W \pm 1%	Resistor	Bourns	CR0603-FX-2202ELF
31	5	SB9, SB10, R16, R17, R24	10 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF1002X
32	5	R18, R19, R20, R21, R26	2 k SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2RKF2001X
33	2	SB2, SB5	0 R SMD 0402 0.1 W \pm 1%	Resistor	Panasonic	ERJ-2GE0R00X
34	3	SB6, SB7, SB8	0 R SMD 0402 0.1 W \pm 1%	Resistors (not mounted)	/	/
35	1	SW1	smd (L 4.6 x W 2.2 x H 1.9 mm)	Reset	C & K	KMR211GLFS

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
36	1	U1	L6984 VDFPN10 (3x3x1.0 mm)	36 V 400 mA synchronous step-down switching regulator	ST	L6984ATR
37	1	U2	LDK220 DFN6 (1.2x1.3x0.5 mm)	200 mA low quiescent current and low noise LDO	ST	LDK220PU33R
38	1	U3	L6362A VFDFPN 12L (3x3x0.90 mm)	IO-Link communication transceiver device IC	ST	L6362ATR
39	1	U4	IIS3DWB LGA-14L (2.5x3x0.83 mm)	Ultra-wide bandwidth, low-noise 3-axis digital accelerometer for industrial applications	ST	IIS3DWBTR
40	1	U5	USBLC6-4SC6 SOT-23-6	Very low capacitance ESD protection	ST	USBLC6-4SC6
41	1	U6	HTS221 HLGA-6L (2x2x0.9 mm)	Capacitive digital sensor for relative humidity and temperature	ST	HTS221TR
42	1	U7	IMP34DT05 HCLGA-4LD (3x4x1 mm)	MEMS audio sensor omnidirectional digital microphone for industrial applications	ST	IMP34DT05TR
43	1	U8	LPS22HB HLGA-10L (2x2x0.76 mm)	Ultra-compact piezoresistive absolute pressure sensor	ST	LPS22HBTR
44	1	U9	M95M01-DF WLCSP8 (2.578x1.716 mm)	1-Mbit SPI bus EEPROM with high-speed clock	ST	M95M01-DFCS6TP/K
45	1	U10	STM32F469AI WLCSP 168L DIE 434 12X14 P 0.4mm	High-performance advanced line, ARM Cortex-M4 core with DSP and FPU	ST	STM32F469AIY6TR
46	1	Y1	32.768 kHz smd (2.05x1.2x0.55mm) ±20ppm	Crystal	NDK	NX2012SA 32.768kHz EXS00A-MU00389
47	1	Y2	24 MHz smd (2x1.6x0.45 mm) ±20ppm	Crystal	NDK	NX2016SA 24.000MHz EXS00A-CS05544
48	1	PCB	50x8.5x1.2mm	PCB	Ermes	-
49	1	NA-supply only	Pitch 1.27 mm, 5x2	SWD Cable	Harwin	M50-9100542

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
50	1	NA-supply only	Pitch 1.27 mm, 5x2	Header Board to Board Connector	GCT	GTC BD030-10-A-A-0350-0300-L-G

Table 3: STEVAL-UKI001V2 bill of materials

Item	Q.ty	Ref.	Part/Value	Description	Manufacturer	Order code
1	2	C1, C2	100 nF, 16 V \pm 20% 0805 (2012 Metric) SMD	Ceramic capacitors	Any	Any
2	1	J1	SWD-10_ENH SMD 10 pos. 1.27 mm	Connector header	Samtec Inc.	FTSH-105-01-L-DV-K-TR
3	1	J2	SWD-14 14 pos. 1.27 mm	Connector header	Samtec Inc.	FTSH-107-01-L-DV-K
4	1	J3	Strip_1X4_SMD 10.16X5.08 mm SMD 4 pos. 2.54 mm	Connector header	Samtec Inc.	TSM-104-01-F-SV-P-TR
5	1	LD1	SML-M13YTT86 20 mA 0805 (2012 Metric) SMD	Yellow LED	Rohm Semiconductor	SML-M13YTT86
6	1	LD2	SML-M13MTT86 20 mA 0805 (2012 Metric) SMD	Green LED	Rohm Semiconductor	SML-M13MTT86
7	2	R1, R2	590 0.125 W, 1/8 W \pm 1% 0805 (2012 Metric) SMD	Chip resistor	Any	Any
8	2	SW1, SW2	SPST-NO 0.05 A 32 V-KMR211GLFS 4.60 mm x 2.80 mm	Tactile switch	C&K	KMR211GLFS
9	1	PCB	FR4-32x25.3x1.6 mm 32x25.3x1.6 mm	PCB	Any	Any

STMicroelectronics**EVALUATION BOARD LICENSE AGREEMENT**

By using this evaluation board or kit (together with all related software, firmware, components, and documentation provided by ST, "Evaluation Board"), You ("You") are agreeing to be bound by the terms and conditions of this Evaluation Board License Agreement ("Agreement"). Do not use the Evaluation Board until You have read and agreed to this Agreement. Your use of the Evaluation Board constitutes Your acceptance of this Agreement.

LICENSE

STMicroelectronics ("ST") grants You the right to use the enclosed Evaluation Board offering limited features only to evaluate and test ST products solely for Your evaluation and testing purposes in a research and development setting. The Evaluation Board shall not be, in any case, directly or indirectly assembled as a part in any production of Yours as it is solely developed to serve evaluation purposes and has no direct function and is not a finished product. If software and/or firmware is accompanied by a separate end user license agreement ("EULA"), then such software and/or firmware shall be governed by such EULA.

EVALUATION BOARD STATUS

The Evaluation Board offers limited features allowing You only to evaluate and test the ST products. The Evaluation Board is not intended for consumer or household use. You are not authorized to use the Evaluation Board in any production system, and it may not be offered for sale or lease, or sold, leased or otherwise distributed for commercial purposes. If the Evaluation Board is incorporated in an evaluation system, the evaluation system may be used by You solely for Your evaluation and testing purposes. Such evaluation system may not be offered for sale or lease or sold, leased or otherwise distributed for commercial purposes and must be accompanied by a conspicuous notice as follows: "This device is not, and may not be, offered for sale or lease, or sold or leased or otherwise distributed for commercial purposes".

OWNERSHIP AND COPYRIGHT

Title to the Evaluation Board remains with ST and/or its licensors. You may not remove any copyright or other proprietary rights notices without prior written authorization from ST. You may make one copy of the software and/or firmware of the Evaluation Board for back up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the software and/or firmware. You agree to prevent any unauthorized copying in whole or in part of the Evaluation Board.

RESTRICTIONS AND WARNINGS

Before You handle or use the Evaluation Board, You must carefully review any related documentation provided by ST. Such documentation may contain important warnings. You shall comply with all such warnings and other instructions and employ reasonable safety precautions in using the Evaluation Board. Failure to do so may result in death, personal injury, or property damage. If You have any questions regarding the safe usage of the Evaluation Board, You should contact ST for guidance. You may not sell, assign, sublicense, lease, rent or otherwise distribute the Evaluation Board for commercial purposes, in whole or in part, or use Evaluation Board in a production system, with the exception that if You are an authorized ST distributor, You may resell the Evaluation Board in compliance with the applicable terms and conditions. Except as provided in this Agreement or as explicitly permitted in the documentation of the Evaluation Board, You may not reproduce the Evaluation Board or modify, reverse engineer, de-compile or disassemble its software and/or firmware, in whole or in part. You shall not use the Evaluation Board in any safety critical or functional safety testing, including but not limited to testing of life supporting, military or nuclear applications. ST expressly disclaims any responsibility for such usage which shall be made at Your sole risk, even if ST has been informed in writing of such usage. Unless expressly designated in writing by ST as suitable for use in testing automotive or aerospace applications, You shall not use the Evaluation Board in such testing.

Notice applicable to Evaluation Boards according to European Regulation

For the European Regulation of the Evaluation Board, the applicable EU directives are considered, with a particular attention to the Low Voltage Directive (LVD) 2014/35/EU, the Electromagnetic Compatibility (EMC) Directive 2014/30/EU, and the Radio Equipment Directive (RED) 2014/53/EU. If the Evaluation Board is outside the scope of the foregoing Directives, then the General Product Safety Directive (GPSD) 2001/95/EC and Council Directive 93/68/EEC, amending Directive 73/23/EEC on electrical equipment designed for use within certain voltage limits, are applicable.

The Evaluation Board meets the requirements of the Restriction of Hazardous Substances (RoHS 2 or RoHS recast) Directive 2011/65/EU, Annex II, as amended by Directive 2015/863/EU.

Notice applicable to Evaluation Boards not FCC-Approved

This kit is designed to allow:

- (1) Product developers to evaluate electronic components, circuitry, or software associated with the kit to determine whether to incorporate such items in a finished product and
- (2) Software developers to write software applications for use with the end product.

This kit is not a finished product and when assembled may not be resold or otherwise marketed unless all required FCC equipment authorizations are first obtained. Operation is subject to the condition that this product not cause harmful interference to licensed radio stations and that this product accept harmful interference. Unless the assembled kit is designed to operate under part 15, part 18 or part 95 of 47 CFR, Chapter I ("FCC Rules"), the operator of the kit must operate under the authority of an FCC license holder or must secure an experimental authorization under part 5 of this chapter.

For Evaluation Boards annotated as FEDERAL COMMUNICATIONS COMMISSION (FCC) Part 15 Compliant

- **FCC Interference Statement for Class A Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.
- **FCC Interference Statement for Class B Evaluation Boards:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
 - Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

WARRANTY

ST WARRANTS THAT IT HAS THE RIGHT TO PROVIDE THE EVALUATION BOARD TO YOU. THIS WARRANTY IS PROVIDED BY ST IN LIEU OF ALL OTHER WARRANTIES, WRITTEN OR ORAL, STATUTORY, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY AS TO MERCHANTABILITY, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE, OR UNINTERRUPTED OR ERROR-FREE OPERATION, ALL OF WHICH ARE EXPRESSLY DISCLAIMED. THE EVALUATION BOARD IS PROVIDED "AS IS".

YOU WARRANT TO ST THAT YOU WILL ENSURE THE EVALUATION BOARD IS USED ONLY BY ELECTRONICS EXPERTS WHO UNDERSTAND THE DANGERS OF HANDLING AND USING SUCH ITEMS, YOU ASSUME ALL RESPONSIBILITY AND LIABILITY FOR ANY IMPROPER OR UNSAFE HANDLING OR USE OF THE EVALUATION BOARD BY YOU, YOUR EMPLOYEES, AFFILIATES, CONTRACTORS, AND DESIGNEES.

LIMITATION OF LIABILITIES

IN NO EVENT SHALL ST BE LIABLE TO YOU, WHETHER IN CONTRACT, TORT (INCLUDING NEGLIGENCE), STRICT LIABILITY, OR ANY OTHER LEGAL THEORY, FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, INCIDENTAL, PUNITIVE, OR EXEMPLARY DAMAGES WITH RESPECT TO ANY MATTERS RELATING TO THIS AGREEMENT, REGARDLESS OF WHETHER ST HAS BEEN ADVISED OF THE POSSIBILITY OF THE SAME. IN NO EVENT SHALL ST'S LIABILITY ARISING OUT OF THIS AGREEMENT IN THE AGGREGATE EXCEED THE AMOUNT PAID BY YOU UNDER THIS AGREEMENT FOR THE PURCHASE OF THE EVALUATION BOARD, OR TEN UNITED STATES DOLLARS (\$10.00) IF NO PURCHASE PRICE WAS PAID.

INDEMNIFICATION

You shall, at Your expense, defend ST and its Affiliates against a claim or action brought by a third party for infringement or misappropriation of any patent, copyright, trade secret or other intellectual property right of a third party to the extent resulting from (1) Your combination of the Evaluation Board with any other component, system, software, or firmware, (2) Your modification of the Evaluation Board, or (3) Your use of the Evaluation Board in a manner not permitted under this Agreement. You shall indemnify ST and its Affiliates against and pay any resulting costs and damages finally awarded against ST or its Affiliates or agreed to in any settlement, provided that You have sole control of the defense and settlement of the claim or action, and ST cooperates in the defense and furnishes all related evidence under its control at Your expense. ST will be entitled to participate in the defense of such claim or action and to employ counsel at its own expense.

"Affiliates" means any corporation or other entity directly or indirectly controlled by, controlling or under common control with the entity in question, for so long as such ownership exists. "Control" means the direct or indirect beneficial ownership of more than fifty (50%) percent of the stock or other equity interests entitled to vote for the election of directors or an equivalent governing body. Any such corporation or other legal entity shall be deemed to be an Affiliate of such Party only as long as such Control exists.

TERMINATION

ST may terminate this Agreement without notice if You breach this Agreement. Upon termination, You shall immediately destroy or return all copies of the software, firmware, and documentation of the Evaluation Board to ST and certify in writing to ST that You have done so.

APPLICABLE LAW AND JURISDICTION

This Agreement shall be governed, construed and enforced in accordance with the laws of Switzerland, without regard to its conflict of laws rules. The UN Convention on Contracts for the International Sale of Goods shall not apply to this Agreement. In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. Any breach of this Agreement by You may result in irreparable damage to ST for which ST will not have an

adequate remedy at law. Accordingly, in addition to any other remedies and damages available, You acknowledge and agree that ST may immediately seek enforcement of this Agreement in any jurisdiction by means of specific performance or injunction, without any requirement to post a bond or other security.

SEVERABILITY

If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement. In addition, any unenforceable or invalid provision shall be deemed replaced by a provision that is valid and enforceable and that comes closest to expressing the intention of the unenforceable or invalid provision.

WAIVER

The waiver by either party of any breach of any provision of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

RELATIONSHIP OF THE PARTIES

Nothing in this Agreement shall create, or be deemed to create, any joint venture, partnership, principal-agent, employer-employee or other relationship between the Parties, except that of independent contractors. Neither Party has the authority or power to bind, to contract in the name of, or to create a liability for the other in any way or for any purpose.

SURVIVAL

Any provision of this Agreement which imposes an obligation after termination of this Agreement shall survive the termination of this Agreement.

SECTION HEADINGS

Section headings are inserted for convenience only and shall not be used to interpret this Agreement.

WASTE AND RECYCLING

The Evaluation Board is not to be disposed of as urban waste. At the end of its life cycle, differentiated waste collection must be followed. Consult the local authorities for more information on the proper disposal channels. It is mandatory to separately collect the Evaluation Board and make sure it is delivered it to the appropriate waste management and recycling centers.

As of 15 August 2018, in all the countries belonging to the European Union, the Evaluation Board is subject to the WEEE Directive 2012/19/EU requirement; therefore, it is forbidden to dispose of the Evaluation Board as undifferentiated waste or with other domestic wastes. Consult the local authorities for more information on the proper recycling centers.

Disposing of the Evaluation Board incorrectly may cause damage to the environment and may be subject to fines based on specific countries' rules.