

Mesh over Bluetooth low energy software expansion for STM32Cube

| | |
|----------------------|--|
| Application | Lighting demo |
| Middleware | BlueNRG Mesh library ST Cryptographic library |
| Hardware Abstraction | STM32Cube Hardware Abstraction Layer (HAL) |
| Hardware | STM32 Nucleo expansion boards X-NUCLEO-IDB05A2 (Connect) X-NUCLEO-BLUENRG2A1 (Sense) |
| | STM32 Nucleo development board |



Features

- Complete software to build Mesh network with Bluetooth low energy (BLE) nodes, extending network coverage to large areas up to 32767 nodes and 126 hops
- Use of BLE enabled smartphones to monitor and control multiple BLE nodes via proxy protocol and legacy BLE GATT connectivity
- Two-layer security, thanks to 128-bit AES CCM encryption and 256-bit ECDH protocol, ensuring protection against multiple attacks, including Replay, Bit-Flipping, Eavesdropping, Man-in-the-Middle and Trashcan
- Supported models include vendor model, partial configuration model, and samples for on-off and level generic models
- Sample implementation available on the [X-NUCLEO-IDB05A2](#) and [X-NUCLEO-BNRG2A1](#) expansion boards connected to a [NUCLEO-L152RE](#), [NUCLEO-L476RG](#), or [NUCLEO-F303RE](#) development board
- Easy portability across different MCU families, thanks to [STM32Cube](#)
- Free, user-friendly license terms

Description

The [X-CUBE-BLEMESH1](#) expansion software package for [STM32Cube](#) runs on the STM32 and provides easy-to-use networking APIs based on a Mesh profile library and a BLE stack.

The expansion is built on [STM32Cube](#) software technology to ease portability across different STM32 microcontrollers.

The software lets you easily create your own application for extending BLE Mesh networks (by offering a ready-to-use Mesh core library), a complete set of compatible APIs, and a lighting reference design demo application running on the [X-NUCLEO-IDB05A2](#) and [X-NUCLEO-BNRG2A1](#) expansion boards connected to a [NUCLEO-L152RE](#), [NUCLEO-L476RG](#) or [NUCLEO-F303RE](#) development board.

| Product summary | |
|--|---|
| Mesh over Bluetooth low energy software expansion for STM32Cube | X-CUBE-BLEMESH1 |
| Bluetooth low energy expansion boards based on the BlueNRG-M0A/BlueNRG-M2SP modules for STM32 Nucleo | X-NUCLEO-IDB05A2 / X-NUCLEO-BNRG2A1 |
| Bluetooth low energy wireless network processor | BlueNRG-MS / BlueNRG-2N |
| STM32 Nucleo development board | STM32 Nucleo |
| Applications | Cloud Connectivity Industrial Tools Wireless Connectivity |

1 Detailed description

1.1 What is STM32Cube?

[STM32Cube](#) is a combination of a full set of PC software tools and embedded software blocks running on STM32 microcontrollers and microprocessors:

- [STM32CubeMX](#) configuration tool for any STM32 device; it generates initialization C code for Cortex-M cores and the Linux device tree source for Cortex-A cores
- [STM32CubeIDE](#) integrated development environment based on open-source solutions like Eclipse or the GNU C/C++ toolchain, including compilation reporting features and advanced debug features
- [STM32CubeProgrammer](#) programming tool that provides an easy-to-use and efficient environment for reading, writing and verifying devices and external memories via a wide variety of available communication media (JTAG, SWD, UART, USB DFU, I2C, SPI, CAN, etc.)
- STM32CubeMonitor family of tools ([STM32CubeMonRF](#), [STM32CubeMonUCPD](#), [STM32CubeMonPwr](#)) to help developers customize their applications in real-time
- [STM32Cube MCU and MPU packages](#) specific to each STM32 series with drivers (HAL, low-layer, etc.), middleware, and lots of example code used in a wide variety of real-world use cases
- [STM32Cube expansion packages](#) for application-oriented solutions

1.2 How does this software complement STM32Cube?

This software is based on the STM32CubeHAL hardware abstraction layer for the STM32 microcontroller. The package extends [STM32Cube](#) by providing a board support package (BSP) for the [X-NUCLEO-IDB05A2](#) and [X-NUCLEO-BNRG2A1](#) expansion boards, and the middleware BLE Mesh library.

The drivers abstract low-level details of the hardware and allow the middleware components and applications to access data in a hardware independent fashion.

The package also includes a sample lighting application that the developer can use to start experimenting with the Mesh library code. To this aim, mobile apps for Android and iOS are available on the respective stores letting you provision, un-provision, create groups and control nodes in the Mesh network using your own BLE enabled smartphone.

Revision history

Table 1. Document revision history

| Date | Version | Changes |
|-------------|---------|---|
| 20-Jun-2018 | 1 | Initial release. |
| 09-Apr-2020 | 2 | Added X-NUCLEO-BNRG2A1 expansion board and NUCLEO-F303RE development board compatibility information. |
| 02-Nov-2020 | 3 | Updated cover page image and product summary table. Added references to X-NUCLEO-IDB05A2. |

IMPORTANT NOTICE – PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries (“ST”) reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST’s terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers’ products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2020 STMicroelectronics – All rights reserved